
Summit Technology's FX3000 Flexible Current Probe offers 10 to 3000 Amp AC current measurements.

Specifications

- 10 to 3000 A_{RMS} AC Current measurement

Accuracy

- 2% of reading +/- 0.2 amps (for currents below 400 A_{RMS}) or +/- 2 Arms (for currents from 400-3000 A_{RMS})

Dimensions

- 24.0 inch Flexible Circumference
- Inside diameter of 7.5 inches
- Outside measurement of 24.0 x .85 inches



Power Requirements

The probe connects directly into PowerSight®. No additional batteries are required.

To order, specify **FX3000**.